

# LED REPLACEMENT TUBES

Replacement LED light tubes are designed to produce higher light output than conventional T8 fluorescent tubes with half the power consumption. The T8 Series also comes with rotating endcaps for directing light where it is needed. LED tubes come complete with LED starter and can be retro fitted into existing or new fluorescent fittings, also ideal for high usage commercial applications or supplied with prewired fittings to suit LED tubes.

Product Code	Voltage (V)	Wattage (W)	Power Factor	Luminous Flux (Lm)	Beam Angle	CRI	Colour temp range	Life span
T8-600-9W	240V AC	10W	>0.95	1190(CW)	130	> 80	3200-6500K	50,000
T8-1200-18W	240V AC	19W	>0.95	2360(CW)	130	> 80	3200-6500K	50,000
T8-1500-25W	240V AC	25W	>0.95	3310(CW)	130	>80	3200-6500K	50,000
NT8-600-9W	240V AC	10W	>0.95	1130(CW)	130	> 80	3200-6500K	50,000
NT8-1200-18W	240V AC	18W	>0.95	2270(CW)	130	> 80	3200-6500K	50,000

